

Illuminated USB microscope **LD6180**

Datasheet

Product description

Handy, Portable, Inexpensive & Light Weight Microscope which can be connected to PC Software Making Inspection and Measurement Immediately!

With the unique optical design, the USB Microscope combines a digital camera, precision optics and LED lighting in the microscope. 40-140X magnification can zoom in on the fine details of surfaces or any too small thing to see.

The USB microscope comes with special software for pictures and movies. With the software measurements can be taken on the length, width, height angle and radius.



Application area's

Automotive, coating industry, laboratory, paint

Features

- Application for those who are involved in inspecting or viewing very small parts.
- Images are clearly shown on the PC screen.
- Easily to adjust between range 40x & 140x magnification
- Built in 4 LED's for operating environment with limited illumination
- Completely portable and an excellent companion to a laptop computer
- Advanced USB interface with true plug&play / hot swapping capabilities
- Snapshot button for instant still image capture

Standard delivery

Illuminated USB microscope, software, USB cable, Quick start guide, Manual

Use

Place the microscope over the object, and easily view the image on your computer screen. Capture images, quickly make measurements by the software. Provide the quick view of specimen-for inspecting anything from biological samples to the finish on machined parts. The measuring software makes it possible the image can be stored, managed, measured and distributed.

Technical specifications

Image sensor	CMOS sensor
Magnification	40x & 140x
Video capture resolution	640x480, 352x288, 340x240, 176x144, 160x120
Still image capture resolution	up to 640x480
Exposure	automatic
Compression	Fixed data Rate hardware Interface Compression Ratio of 4:1, 6:1, 8:1
Video data format	RGB24
Power supply	USB interface supplied power

PC Interface	USB 1.1
Video transfer rate	30fps @ CIF (320x240) 12,5fps @ VGA (640x480)
Snapshot button	Hardware
Supports	Win 98, WIn 2000, Win CE, Win XP
System Requirements:	<ul style="list-style-type: none"> • Pentium III 500MHZ or greater • Windows 2000/XP • Direct X9 or greater • Internet Explorer 5 or greater • Available USB port

Special care

Use a damp soft cloth to clean. Don't use solvents or abrasives.

Disclaimer

The information given in this sheet is not intended to be exhaustive and any person using the product for any purpose other than that specifically recommended in this sheet without first obtaining written confirmation from us as to the suitability of the product for the intended purpose does so at his own risk. Whilst we endeavour to ensure that all advice we give about the product (whether in this sheet or otherwise) is correct we have no control over either the quality or condition of the product or the many factors affecting the use and application of the product. Therefore, unless we specifically agree in writing to do so, we do not accept any liability whatsoever or howsoever arising for the performance of the product or for any loss or damage (other than death or personal injury resulting from our negligence) arising out of the use of the product. The information contained in this sheet is liable to modification from time to time in the light of experience and our policy of continuous product development.

